

Pure Sine Wave Inverter 12V DC 600W RCD



12V compatibility producing 230V AC Pure Sine Wave with 600W of power

Will work with all 12V vehicles to produce 230V mains power with 600W of power for all electronic devices including sensitive devices, for remote working



1. 1200W peak power rating. 2. RCD Protected

1. To handle large power loads when initially starting an electrical device. Will drop back down to 600W continuous supply. 2. The integral Residual Current Device (RCD) replaces the need for an external RCD and will switch off the inverter in the event a fault is detected between live and earth. This protects the user against electric shocks.



2.1A USB Charging port

To charge mobile phones or smaller electronic devices at the same time as using the main power supply from the inverter.



Low battery alarm at 10V and low battery shutdown at 9.5V

Low battery alarm to alert operators to the fact that their vehicle battery is being drained and should stop using the inverter. When a vehicle's battery drops below 9.5V the inverter will switch off to preserve the vehicle battery to allow the vehicle to restart.



High-quality inverters for off-grid power needs

OSRAM POWERinvert PRO is an extensive range of professional heavy duty inverters for remote working. Available in either Pure Sine Wave or Modified Sine Wave for both 12V and 24V applications. OSRAM POWERinvert Pro inverters take the 12V or 24V DC vehicle electrical supply and invert into 230V AC mains power to run and operate electrical equipment from service vehicles. Pure Sine Wave Inverters produce a sine wave with the same frequency as mains power, with no distortion, to power sensitive electronics. Modified Inverters have distorted frequency, meaning they will power less complicated products such as fridges and power tools.

Product family datasheet

Technical data

	Product information	Electrical Data		
Product description	Number Of Phases	Input voltage range	Continuous Power Rating (up to 12 hours)	Output voltage
Pure Sine Wave Inverter 12V DC 600W	Single	(12V NOM) 9.5 V - 16.5 V	600 W	200 - 240 Vrms

Product description	No Load Current	Peak Power Rating (up to 200ms)	Input Current	Peak Amps
Pure Sine Wave Inverter 12V DC 600W	< 1.5 A	2 * rated power for 0.2s	59 A	118

	Physical Attributes & Dimensions	Dimensions & weight	Lifetime Data	Programmable features
Product description	Height	Input Cable Gauge / Length	Guarantee	Thermal Protection
Pure Sine Wave Inverter 12V DC 600W	90.0 mm	600mm, 14mm^2	2 years	Yes

	Certificates & standards	Environmental & Regulatory Information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)		
Product description	Standards	Primary article identifier	Candidate list substance 1	CAS No. of substance 1
Pure Sine Wave Inverter 12V DC 600W	CE / E- Mark	4052899631045	Lead	7439-92-1

Product description	Safe use instruction	Declaration no. in SCIP database
Pure Sine Wave Inverter 12V DC 600W	The identification of the Candidate List substance is sufficient to allow safe use of the article.	9b1254d7-0516-44c3-b467-54ae5d91b019

Download Data

File	
	User instruction POWERinvert PRO Pure Sine Wave Inverter

Safety advice

Tested and certified to the relevant EMC and LVD Directives.

Legal advice

CE Approved

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.