


6.6A 64341 HLX-A 100-15 PK30D



Product features and benefits

- Low maintenance costs due to long lamp life
- Reliable and consistent light output enhances visibility over the life of the lamp
- FAA approved in conjunction with many OEM fixtures
- Durable construction provides resistance to the effects of vibration
- Broad product portfolio for runway, taxiway, and approach lighting
- IR radiation provides guidance in low visibility conditions
- Flicker-free operation
- Ability to reduce light output when needed
- Mercury-free

Areas of application

- Airfield Lighting

Product datasheet

Technical data

General product information

Product Number	59072
Product Name	66A64341HLXA10015PK30D 100/CS 1/SKU
Ordering Abbreviation	6.6A 64341 HLX-A 100-15 PK30D
Brand Name	OSRAM
General Description	100 watt, tungsten halogen, current controlled, single-ended, airfield
Application	Airfield/Airport
LIF Code	J1/79

Electrical data

Nominal Wattage	100 W
Nominal Voltage	15.2 V
Current (A)	6.6 A

Light technical data

Light Center Length - LCL (in)	0.787 in
Light Center Length - LCL (mm)	20 mm

Physical attributes

Base	GZ9.5
Bulb Shape	T13,5
Maximum Overall Length (in)	1.890 in
Maximum Overall Length (mm)	48 mm
Diameter d (in)	0.531 in
Diameter d (mm)	13.50 mm
Filament	C BAR 6
Filament Dimensions Length (in)	0.1180 in
Filament Dimensions Length (mm)	3 mm
Filament Dimensions Width (in)	0.209 in
Filament Dimensions Width (mm)	5.3 mm

Additional product data

Class	C (gas)
Lamp Type	SINGLE ENDED

Packaging Information

Product datasheet

Product number	EAN/UPC	Packaging	Quantity	Outside dimensions L x w x h	Gross weight
59072	4008321345639	Folding box (SKU)	1	1.3 in x 1.5 in x 2.7 in	0.1 lb
59072	10046135590723	Shipping box (Case)	100	13.4 in x 7.5 in x 6.1 in	5 lb

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Disclaimer

OSRAM does not accept liability for errors, changes and omissions.